

FINE 1512/156C AL通道表

中文通道表

| 通道 | RGBW | Pixie | HSI | CMY | CCT | RGB |
|-----|---------|---------------|---------|---------|---------|-----|
| 1 | 功能 | 功能 | 功能 | 功能 | 功能 | 功能 |
| 2 | R | 调光 | 色调 | C | 调光 | R |
| 3 | G | 频闪 | H微调 | M | 色温 | G |
| 4 | B | R1 | 饱和度 | Y | 频闪 | B |
| 5 | W | G1 | 亮度 | 亮度 | 色轮&色彩渐变 | |
| 6 | 调光 | B1 | 频闪 | 频闪 | 宏效果&速度 | |
| 7 | 频闪 | W1 | 色轮&色彩渐变 | 色轮&色彩渐变 | 宏功背景色 | |
| 8 | 色轮&色彩渐变 | . | 宏效果&速度 | 宏效果&速度 | | |
| 9 | 宏效果&速度 | . | 宏功背景色 | 宏功背景色 | | |
| 10 | 宏功背景色 | . | | | | |
| ... | | . | | | | |
| ... | | . | | | | |
| 24 | | R6 (1512/156) | | | | |
| 25 | | G6 (1512/156) | | | | |
| 26 | | B6 (1512/156) | | | | |
| 27 | | W6 (1512/156) | | | | |
| ... | | ... (1512) | | | | |
| 48 | | R12 (1512) | | | | |
| 49 | | G12 (1512) | | | | |
| 50 | | B12 (1512) | | | | |
| 51 | | W12 (1512) | | | | |

| | | | | | | | | | | | | |
|---------|------|-------------------------|---------|-------|-------|----|-------|---|-------|----|-------|----|
| RGBW | ch1 | 功能(*此功能 设置需延时3 秒) | 0-5 | N/A | | | | | | | | |
| | | | 6-15 | RGBW | | | | | | | | |
| | | | 16-25 | Pixie | | | | | | | | |
| | | | 26-35 | HSI | | | | | | | | |
| | | | 36-45 | CMY | | | | | | | | |
| | | | 46-55 | CCT | | | | | | | | |
| | | | 56-65 | RGB | | | | | | | | |
| | | | 66-199 | N/A | | | | | | | | |
| | | | 200-204 | DIM2 | | | | | | | | |
| | | | 205-209 | DIM1 | | | | | | | | |
| | | | 210-214 | DIMO | | | | | | | | |
| | | | 215-219 | N/A | | | | | | | | |
| | | | 220-214 | N/A | | | | | | | | |
| | | | 215-255 | N/A | | | | | | | | |
| | ch2 | 红光 | 0-255 | | | | | | | | | |
| | | | ch3 | 绿光 | 0-255 | | | | | | | |
| | | | | | ch4 | 蓝光 | 0-255 | | | | | |
| | | | | | | | ch5 | 白 | 0-255 | | | |
| | | | | | | | | | ch6 | 亮度 | 0-255 | |
| | | | | | | | | | | | ch7 | 频闪 |
| 6-105 | 标准频闪 | | | | | | | | | | | |
| 106-110 | 无 | | | | | | | | | | | |
| 110-179 | 雷电频闪 | | | | | | | | | | | |
| 180-185 | 无 | | | | | | | | | | | |
| 186-255 | 随机频闪 | | | | | | | | | | | |
| ch8 | 色轮 | 0-5 | N/A | | | | | | | | | |
| | | 6-255 | 色轮1-65 | | | | | | | | | |

| | | | | |
|--|------|-------|-------|-------|
| | ch9 | 宏功能 | 0-5 | N/A |
| | | | 6-255 | 宏1-25 |
| | ch10 | 宏功背景色 | 0-255 | HSI方式 |

| | | | | |
|-----|---------|-------------------------|---------|-------|
| RGB | ch1 | 功能(*此功能 设置需延时3 秒) | 0-5 | N/A |
| | | | 6-15 | RGBW |
| | | | 16-25 | Pixie |
| | | | 26-35 | HSI |
| | | | 36-45 | CMY |
| | | | 46-55 | CCT |
| | | | 56-65 | RGB |
| | | | 66-199 | N/A |
| | | | 200-204 | DIM2 |
| | | | 205-209 | DIM1 |
| | | | 210-214 | DIM0 |
| | | | 215-219 | N/A |
| | | | 220-214 | N/A |
| | 215-255 | N/A | | |
| | ch2 | 红色 | 0-255 | |
| ch3 | 绿色 | 0-255 | | |
| ch4 | 蓝色 | 0-255 | | |

| | | | | |
|---------|---------|-------------------------|---------|-------|
| HSI | ch1 | 功能(*此功能 设置需延时3 秒) | 0-5 | N/A |
| | | | 6-15 | RGBW |
| | | | 16-25 | Pixie |
| | | | 26-35 | HSI |
| | | | 36-45 | CMY |
| | | | 46-55 | CCT |
| | | | 56-65 | RGB |
| | | | 66-199 | N/A |
| | | | 200-204 | DIM2 |
| | | | 205-209 | DIM1 |
| | | | 210-214 | DIM0 |
| | | | 215-219 | N/A |
| | | | 220-214 | N/A |
| | 215-255 | N/A | | |
| | ch2 | 色调 | 0-255 | |
| | ch3 | 色调微调 | 0-255 | |
| | ch4 | 色度 | 0-255 | |
| | ch5 | 亮度 | 0-255 | |
| | ch6 | 频闪 | 0-5 | 无 |
| | | | 6-105 | 标准频闪 |
| | | | 106-110 | 无 |
| | | | 110-179 | 雷电频闪 |
| | | | 180-185 | 无 |
| 186-255 | 随机频闪 | | | |
| ch7 | 色轮 | 0-5 | N/A | |
| | | 6-255 | 色轮1-65 | |
| ch8 | 宏功能 | 0-5 | N/A | |
| | | 6-255 | 宏1-25 | |
| ch9 | 宏功背景色 | 0-255 | HSI方式 | |

| | | | | |
|--|--|--|-----|-----|
| | | | 0-5 | N/A |
|--|--|--|-----|-----|

| | | | | | | |
|-------|---------|-------------------------|---------|-------|-------|-----|
| PIXI | ch1 | 功能(*此功能 设置需延时3 秒) | 6-15 | RGBW | | |
| | | | 16-25 | Pixie | | |
| | | | 26-35 | HSI | | |
| | | | 36-45 | CMY | | |
| | | | 46-55 | CCT | | |
| | | | 56-65 | RGB | | |
| | | | 66-199 | N/A | | |
| | | | 200-204 | DIM2 | | |
| | | | 205-209 | DIM1 | | |
| | | | 210-214 | DIMO | | |
| | | | 215-219 | N/A | | |
| | | | 220-214 | N/A | | |
| | | | 215-255 | N/A | | |
| | | | CH2 | 亮度 | 0-255 | 总调光 |
| | | | ch3 | 频闪 | 0-5 | 无 |
| | 6-105 | 标准频闪 | | | | |
| | 106-110 | 无 | | | | |
| | 110-179 | 雷电频闪 | | | | |
| | 180-185 | 无 | | | | |
| | 186-255 | 随机频闪 | | | | |
| ch4 | 红色1 | 0-255 | | | | |
| ch5 | 绿色1 | 0-255 | | | | |
| ch6 | 蓝色1 | 0-255 | | | | |
| ch7 | 白色1 | 0-255 | | | | |
| | | | | | | |
| ch48 | 红色12 | 0-255 | | | | |
| ch49 | 绿色12 | 0-255 | | | | |
| ch50 | 蓝色12 | 0-255 | | | | |
| ch51 | 白色12 | 0-255 | | | | |

| | | | | |
|---------|-----|-------------------------|---------|-------|
| CMY | ch1 | 功能(*此功能 设置需延时3 秒) | 0-5 | N/A |
| | | | 6-15 | RGBW |
| | | | 16-25 | Pixie |
| | | | 26-35 | HSI |
| | | | 36-45 | CMY |
| | | | 46-55 | CCT |
| | | | 56-65 | RGB |
| | | | 66-199 | N/A |
| | | | 200-204 | DIM2 |
| | | | 205-209 | DIM1 |
| | | | 210-214 | DIMO |
| | | | 215-219 | N/A |
| | | | 220-214 | N/A |
| | | | 215-255 | N/A |
| | | | ch2 | 亮度 |
| | ch3 | C | 0-255 | 青色 |
| | ch4 | M | 0-255 | 洋红色 |
| | ch5 | Y | 0-255 | 黄色 |
| | ch6 | 频闪 | 0-5 | 无 |
| | | | 6-105 | 标准频闪 |
| 106-110 | | | 无 | |
| 110-179 | | | 雷电频闪 | |
| 180-185 | | | 无 | |

| | | | | |
|--|-----|-------|---------|--------|
| | | | 186-255 | 随机频闪 |
| | ch7 | 色轮 | 0-5 | N/A |
| | | | 6-255 | 色轮1-65 |
| | ch8 | 宏功能 | 0-5 | N/A |
| | | | 6-255 | 宏1-25 |
| | ch9 | 宏功背景色 | 0-255 | HSI方式 |

| | | | | |
|-----|-------|-------------------------|---------|-------------|
| CCT | ch1 | 功能(*此功能 设置需延时3 秒) | 0-5 | N/A |
| | | | 6-15 | RGBW |
| | | | 16-25 | Pixie |
| | | | 26-35 | HSI |
| | | | 36-45 | CMY |
| | | | 46-55 | CCT |
| | | | 56-65 | RGB |
| | | | 66-199 | N/A |
| | | | 200-204 | DIM2 |
| | | | 205-209 | DIM1 |
| | | | 210-214 | DIM0 |
| | | | 215-219 | N/A |
| | | | 220-214 | N/A |
| | | | 215-255 | N/A |
| | ch2 | 亮度 | 0-255 | |
| | ch3 | 色温 | 0-5 | 6500K |
| | | | 6-15 | 5600K |
| | | | 16-25 | 4300K |
| | | | 26-35 | 3200K |
| | | | 36-255 | 2600-10000K |
| | ch4 | 频闪 | 0-5 | 无 |
| | | | 6-105 | 标准频闪 |
| | | | 106-110 | 无 |
| | | | 110-179 | 雷电频闪 |
| | | | 180-185 | 无 |
| | | | 186-255 | 随机频闪 |
| | ch5 | 色轮 | 0-5 | N/A |
| | | | 6-255 | 色轮1-65 |
| ch6 | 宏功能 | 0-5 | N/A | |
| | | 6-255 | 宏1-25 | |
| ch7 | 宏功背景色 | 0-255 | HSI方式 | |